

DEVICE SPECIFICATIONS

NI PXIe-4300

This document lists specifications for the NI PXIe-4300 module. These specifications are typical for the range of 0 °C to 55 °C unless otherwise stated. The system must be allowed to warm up for 15 minutes to achieve the rated accuracy. All specifications are subject to change without notice. Visit ni.com/manuals for the most current specifications and product documentation.



Note Keep the filler panels on all unused slots in your chassis to maintain forced air cooling.



Caution Maximum voltage for all analog inputs is ± 11 V for all ranges.

Analog Input

Number of channels.....	8 differential
ADC resolution.....	16 bits
DNL.....	No missing codes guaranteed
INL.....	Refer to the <i>AI Absolute Accuracy (Specification)</i> section.
Sampling rate	
Maximum.....	250 kS/s per channel
Minimum.....	No minimum
Timing accuracy.....	50 ppm of sample rate
Timing resolution.....	10 ns
Input coupling.....	DC
Voltage measurement range (software-selectable per channel).....	± 10 V, ± 5 V, ± 2 V, ± 1 V

Maximum working voltage (signal + common mode)

Maximum Working Voltage (Signal + Common Mode)	
Range	Working Voltage
10 V	±11 V
5 V	±10.5 V
2 V	±9 V
1 V	±8.5 V

CMRR from COM (to 60 Hz)

10 V..... 95 dB
 5 V..... 100 dB
 2 V, 1 V 105 dB

Bandwidth..... 520 kHz

Filtering

Lowpass (software-selectable per channel)..... 10 kHz, 100 kHz, disable
 Cut-off frequency tolerance±5%
 Filter type2nd order Butterworth

Input impedance

Device on¹
 AI- to AI COM >1 GΩ in parallel with 10 pF
 AI+ to AI COM..... >1 GΩ in parallel with 10 pF
 Device off
 AI+ to AI COM..... 10 kΩ
 AI- to AI COM 10 kΩ

Input bias current±6 nA

Input FIFO size 2,046 samples shared among channels used

Data transfers DMA (scatter-gather), programmed I/O

Fault protection (powered on)

Between AI+ and AI-.....±60 V
 Between any AI and COM.....±60 V
 Between PFI or RSVD lines and COM±24 V

Input current during fault conditions±5 mA max/AI pin

¹ The impedance given is for the NI PXIe-4300. Refer to the *NI PXIe-4300 and TB-4300/B/C User Guide and Terminal Block Specifications* for terminal block impedance information.

AI Absolute Accuracy (Specification)

INL error..... 76 ppm of range

Nominal Range		Residual Gain Error (ppm of Reading)	Residual Offset Error (ppm of Range)	Offset Tempco (ppm of Range/°C)	Random Noise, σ (μ Vrms)	Absolute Accuracy at Full Scale (μ V)
Positive Full Scale	Negative Full Scale					
10	-10	65	33	10	208	2,460
5	-5	69	68	10	107	1,430
2	-2	75	168	11	58	785
1	-1	88	337	11	50	575



Note Accuracies listed are valid for up to one year from the module external calibration.

Stability

Gain drift..... 11.5 ppm/°C

Reference drift 5 ppm/°C

AI Absolute Accuracy Equation

$$AbsoluteAccuracy = Reading \cdot (GainError) + Range \cdot (OffsetError) + NoiseUncertainty$$

$$GainError = ResidualAIGainError + GainTempco \cdot (TempChangeFromLastInternalCal) + ReferenceTempco \cdot (TempChangeFromLastExternalCal)$$

$$OffsetError = ResidualAIOffsetError + OffsetTempco \cdot (TempChangeFromLastInternalCal) + INL_Error$$

$$NoiseUncertainty = \frac{RandomNoise \cdot 3}{\sqrt{10000}}$$

For a coverage factor of 3 sigma and averaging 10000 points.

AI Absolute Accuracy Example

Absolute accuracy at full scale on the analog input channels is determined using the following assumptions:

- $TempChangeFromLastExternalCal = 10\text{ }^{\circ}\text{C}$
- $TempChangeFromLastInternalCal = 1\text{ }^{\circ}\text{C}$
- $number_of_readings = 10000$
- $CoverageFactor = 3\sigma$

For example, on the 10 V range, the absolute accuracy at full scale is as follows:

$$GainError = 65\text{ ppm} + 11.5\text{ ppm} \cdot 1\text{ }^{\circ}\text{C} + 5\text{ ppm} \cdot 10\text{ }^{\circ}\text{C} = 126.5\text{ ppm}$$

$$OffsetError = 33\text{ ppm} + 10\text{ ppm} \cdot 1\text{ }^{\circ}\text{C} + 76\text{ ppm} = 119\text{ ppm}$$

$$NoiseUncertainty = \frac{208\text{ }\mu\text{V} \cdot 3}{\sqrt{10000}} = 6.2\text{ }\mu\text{V}$$

$$AbsoluteAccuracy = 10\text{ V} \cdot (GainError) + 10\text{ V} \cdot (OffsetError) + NoiseUncertainty = 2,460\text{ }\mu\text{V}$$

Digital PFI Input

Electrical Characteristics

Level	Min	Max
Input high voltage (VIH)	1.87 V	5.5 V
Input low voltage (VIL)	0 V	0.84 V
Hysteresis	0.56 V	0.87 V

Triggers

Analog Trigger

Source	AI<0..7>
Purpose.....	Reference Trigger
Level	Full Scale (depending on AiRange), Programmable
Resolution	16-bit
Mode	Rising-edge, Rising-edge with Hysteresis, Falling-edge, Falling-edge with Hysteresis, Entering Window, Leaving Window

Digital Trigger

Source	PXI_TRIG<0..7>, PXI_STAR, PXIe_DSTAR<A..B> PFI<0..1>
Purpose	Start Trigger, Reference Trigger, Pause Trigger
Polarity.....	Software-selectable
Debounce Filter Settings	Disable, 90 ns, 5.12 μs, 2.56 ms, Custom interval

Clocking

Source	Onboard Clock, PXI_TRIG<0..7>, PXI_STAR, PXIe_DSTAR<A..B>, PFI<0..1>, PXIe_Clk100 (RefClk Only)
Destination.....	Sample Clock, Sample Clock Timebase, Reference Clock
Polarity.....	Software-selectable (except Reference Clock)
Debounce filter settings (Sample Clock Only).....	Disable, 90 ns, 5.12 μs, 2.56 ms, Custom interval

Reference clock locking frequencies

Reference Signal	Locking Input Frequency (MHz)		
	10	20	100
PXIe_DSTAR<A.. B>	✓	✓	✓
PXI_STAR	✓	✓	—
PXIe_Clk100	—	—	✓
PXI_TRIG<0..7>	✓	✓	—
PFI<0..1>	✓	✓	—



Note National Instruments does not recommend locking to non-selected frequencies.

Output Timing Signals

Source	Start Trigger, Reference Trigger, Pause Trigger, PFI<0..1>, Sample Clock, Various Derived Timebases and Clocks
Destination	PXI_TRIG<0..7> PXIe_DSTAR C
Polarity	Software-selectable

Bus Interface

Form factor	x1 PXI Express peripheral module, specification rev 1.0 compliant
Slot compatibility	PXI Express or PXI Express hybrid slots
DMA channels	1 analog input

Calibration

Recommended warm-up time	15 minutes
Calibration interval	1 year

Power Requirements

+3.3 V	2.0 W
+12 V	8.8 W

Physical Requirements

Dimensions	Standard 3U PXIe, 16 cm by 10 cm (6.3 in. by 3.9 in.)
Weight	148 g (5.2 oz)
I/O connector	96-pin male DIN 41612/IEC 60603-2 connector.

Environmental Specifications

Maximum altitude.....	2,000 m (800 mbar), at 25 °C ambient temperature
Pollution Degree	2
Indoor use only	

Operating Environment

Ambient temperature range	0 °C to 55 °C (Tested in accordance with IEC-60068-2-1 and IEC-60068-2-2. Meets MIL-PRF-28800F Class 3 low temperature limit and MIL-PRF-28800F Class 2 high temperature limit.)
Relative humidity range.....	10% to 90%, noncondensing (Tested in accordance with IEC-60068-2-56.)

Storage Environment

Ambient temperature range	-40 °C to 71 °C (Tested in accordance with IEC-60068-2-1 and IEC-60068-2-2. Meets MIL-PRF-28800F Class 3 limits.)
Relative humidity range.....	5% to 95% noncondensing (Tested in accordance with IEC-60068-2-56.)

Shock and Vibration

Operating shock.....	30 g peak, half-sine, 11 ms pulse (Tested in accordance with IEC-60068-2-27. Meets MIL-PRF-28800F Class 2 limits.)
Random vibration	
Operating	5 Hz to 500 Hz, 0.3 g _{rms}
Non-operating.....	5 Hz to 500 Hz, 2.4 g _{rms} (Tested in accordance with IEC-60068-2-64. Nonoperating test profile exceeds the requirements of MIL-PRF-28800F, Class 3.)

Safety Voltage

Connect only voltages that are within the following limits:

Between any AI+ and AI-±11 V

Between any AI terminal and COM±11 V

Isolation

Channel to channel

Continuous 300 Vrms, Measurement Category II (Basic)

Withstand 1,400 Vrms

Channel to earth ground

Continuous 300 Vrms, Measurement Category II

Withstand 2,300 Vrms, verified by a 5 s dielectric
withstand test



Caution Do *not* use for measurements within Measurement Categories III or IV.



Caution The protection provided by the NI PXIe-4300 can be impaired if it is used in a manner not described in this document.

Safety

This product meets the requirements of the following standards of safety for electrical equipment for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1



Note For UL and other safety certifications, refer to the product label or the [Online Product Certification](#) section.

Electromagnetic Compatibility

This product meets the requirements of the following EMC standards for electrical equipment for measurement, control, and laboratory use:

- EN 61326-1 (IEC 61326-1): Class A emissions; Basic immunity
- EN 55011 (CISPR 11): Group 1, Class A emissions
- AS/NZS CISPR 11: Group 1, Class A emissions
- FCC 47 CFR Part 15B: Class A emissions
- ICES-001: Class A emissions



Note In the United States (per FCC 47 CFR), Class A equipment is intended for use in commercial, light-industrial, and heavy-industrial locations. In Europe, Canada, Australia and New Zealand (per CISPR 11) Class A equipment is intended for use only in heavy-industrial locations.



Note Group 1 equipment (per CISPR 11) is any industrial, scientific, or medical equipment that does not intentionally generate radio frequency energy for the treatment of material or inspection/analysis purposes.



Note For EMC declarations and certifications, and additional information, refer to the [Online Product Certification](#) section.

CE Compliance

This product meets the essential requirements of applicable European Directives as follows:

- 2014/35/EU; Low-Voltage Directive (safety)
- 2014/30/EU; Electromagnetic Compatibility Directive (EMC)

Online Product Certification

Refer to the product Declaration of Conformity (DoC) for additional regulatory compliance information. To obtain product certifications and the DoC for this product, visit ni.com/certification, search by model number or product line, and click the appropriate link in the Certification column.

Environmental Management

NI is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial to the environment and to NI customers.

For additional environmental information, refer to the *Minimize Our Environmental Impact* web page at ni.com/environment. This page contains the environmental regulations and directives with which NI complies, as well as other environmental information not included in this document.

Waste Electrical and Electronic Equipment (WEEE)



EU Customers At the end of the product life cycle, all products *must* be sent to a WEEE recycling center. For more information about WEEE recycling centers, National Instruments WEEE initiatives, and compliance with WEEE Directive 2002/96/EC on Waste and Electronic Equipment, visit ni.com/environment/weee.

电子信息产品污染控制管理办法（中国 RoHS）



中国客户 National Instruments 符合中国电子信息产品中限制使用某些有害物质指令 (RoHS)。关于 National Instruments 中国 RoHS 合规性信息，请登录 ni.com/environment/rohs_china。(For information about China RoHS compliance, go to ni.com/environment/rohs_china.)

Refer to the *NI Trademarks and Logo Guidelines* at ni.com/trademarks for more information on NI trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering NI products/technology, refer to the appropriate location: **Help** » **Patents** in your software, the `patents.txt` file on your media, or the *National Instruments Patents Notice* at ni.com/patents. You can find information about end-user license agreements (EULAs) and third-party legal notices in the `readme` file for your NI product. Refer to the *Export Compliance Information* at ni.com/legal/export-compliance for the NI global trade compliance policy and how to obtain relevant HTS codes, ECCNs, and other import/export data. NI MAKES NO EXPRESS OR IMPLIED WARRANTIES AS TO THE ACCURACY OF THE INFORMATION CONTAINED HEREIN AND SHALL NOT BE LIABLE FOR ANY ERRORS. U.S. Government Customers: The data contained in this manual was developed at private expense and is subject to the applicable limited rights and restricted data rights as set forth in FAR 52.227-14, DFAR 252.227-7014, and DFAR 252.227-7015.

© 2010–2015 National Instruments. All rights reserved.