

SPECIFICATIONS

NI 5753

16-Bit, 120 MS/s, 12 Channel DC/16 Channel AC Receiver Adapter Module

This document lists specifications for the NI 5753 adapter module. Pair these specifications with the specifications listed in your FlexRIO FPGA module specifications document or your Controller for FlexRIO specifications document.



Caution The protection provided by the NI 5753 can be impaired if it is used in a manner not described in this document.



Caution To avoid permanent damage to the NI 5753, disconnect all signals connected to the NI 5753 before powering down the module, and only connect signals after the module has been powered on by the FlexRIO FPGA module or the Controller for FlexRIO.



Note All numeric specifications are typical unless otherwise noted. All graphs illustrate the performance of a representative module.

Specifications are subject to change without notice. For the most recent device specifications, visit ni.com/manuals.

Contents

FlexRIO Documentation.....	2
General Characteristics.....	4
Typical Specifications.....	4
Analog Input Levels.....	4
AC-Coupled Performance.....	5
DC-Coupled Performance.....	6
DC Power Requirements.....	8
Current Requirements.....	8
Voltage Requirements.....	8
CLK IN.....	9
Internal Clock.....	9
AUX I/O (Port 0 DIO <0..3>, Port 1 DIO <0..3>, and PFI <0..3>).....	10
Power Draw.....	10
Physical.....	10
Environment.....	11
Operating Environment.....	11
Storage Environment.....	11

Shock and Vibration.....	11
Compliance and Certifications.....	12
Safety.....	12
Electromagnetic Compatibility.....	12
CE Compliance	12
Online Product Certification.....	13
Environmental Management.....	13

FlexRIO Documentation

Table 1. FlexRIO Documentation Locations and Descriptions

Document	Location	Description
Getting started guide for your FlexRIO FPGA module or Controller for FlexRIO	Available from the Start menu and at ni.com/manuals .	Contains installation instructions for your FlexRIO system.
Specifications document for your FlexRIO FPGA module or Controller for FlexRIO	Available from the Start menu and at ni.com/manuals .	Contains specifications for your FlexRIO FPGA module or Controller for FlexRIO.
Getting started guide for your adapter module	Available from the Start menu and at ni.com/manuals .	Contains signal information, examples, and CLIP details for your adapter module.
Specifications document for your adapter module	Available from the Start menu and at ni.com/manuals .	Contains specifications for your adapter module.
<i>LabVIEW FPGA Module Help</i>	Embedded in <i>LabVIEW Help</i> and at ni.com/manuals .	Contains information about the basic functionality of the LabVIEW FPGA Module.

Table 1. FlexRIO Documentation Locations and Descriptions (Continued)

Document	Location	Description
<i>Real-Time Module Help</i>	Embedded in <i>LabVIEW Help</i> and at ni.com/manuals .	Contains information about real-time programming concepts, step-by-step instructions for using LabVIEW with the Real-Time Module, reference information about Real-Time Module VIs and functions, and information about LabVIEW features on real-time operating systems.
<i>FlexRIO Help</i>	Available from the Start menu and at ni.com/manuals .	Contains information about the FPGA module front panel connectors and I/O, controller for FlexRIO front panel connectors and I/O, programming instructions, and adapter module component-level IP (CLIP).
<i>FlexRIO Adapter Module Development Kit User Manual</i>	Available from the Start menu at Start»All Programs»National Instruments»NI FlexRIO»NI FlexRIO Adapter Module Development Kit»Documentation .	Contains information about how to create custom adapter modules for use with FlexRIO FPGA modules.
LabVIEW Examples	Available in NI Example Finder. In LabVIEW, click Help»Find Examples»Hardware Input and Output»FlexRIO .	Contains examples of how to run FPGA VIs and Host VIs on your device.
IPNet	Located at ni.com/ipnet .	Contains LabVIEW FPGA functions and intellectual property to share.
FlexRIO product page	Located at ni.com/flexrio .	Contains product information and data sheets for FlexRIO devices.

General Characteristics

Number of channels

DC-coupled	12 analog input
AC-coupled	16 analog input
Input impedance	50 Ω
Sample rate	120 MS/s
Frequency range	
DC-coupled	DC to 250 MHz
AC-coupled	0.1 MHz to 250 MHz
ADC type	AD9653 ¹

Related Information

[Refer to www.analog.com](http://www.analog.com) for more information about the AD9653.

Typical Specifications

Analog Input Levels

ADC offset error ($2 V_{pp}$ input) ²	-6 mV
Uncalibrated DC coupling offset error ³	± 10 mV
ADC gain error	-5% full scale
DC offset control (DC-coupled option)	
Range (at input)	-0.5 V to 0.5 V
Resolution	500 μ V/step
Full-scale input (0 dBFS, 50 Ω , 20.1 MHz)	
AC-coupled build	
Number of channels	16
Input voltage	1.8 V_{pp}
Input power	+9.1 dBm

¹ The AC-coupled version uses four AD9653 to implement 16 channels. The DC-coupled version uses three AD9653 to implement 12 channels.

² ADC offset dominates when AC-coupled, does not include offset compensation.

³ Typical DC offset due to component tolerance, does not include system DC variation.

DC-coupled build

Number of channels	12
Input voltage	0.9 V _{pp}
Input power	+3.2 dBm

AC-Coupled Performance

Bandwidth

-3 dB	1 MHz to 176 MHz
-1 dB	1 MHz to 85 MHz

SNR⁴

20.17 MHz input	75.86 dBFS
70.17 MHz input	70.75 dBFS
124.17 MHz input	66.09 dBFS

SINAD⁴

20.17 MHz input	75.8 dBFS
70.17 MHz input	70.56 dBFS
124.17 MHz input	65.95 dBFS

SFDR⁴

20.17 MHz input	-94.03 dBc
70.17 MHz input	-84.84 dBc
124.17 MHz input	-79.52 dBc

RX channel to RX channel isolation⁵

1 MHz	86 dB
50 MHz	77 dB
100 MHz	71 dB
150 MHz	68 dB
200 MHz	64 dB

⁴ Measured with a 120 MHz onboard Sample Clock and a -1 dBFS input signal.

⁵ Worst adjacent channel with -1 dBFS input.

Figure 1. AC-Coupled Passband





Figure 2. Analog Input One-Tone Spectral Measurement (20.17 MHz, -1 dBFS)



DC-Coupled Performance

Bandwidth

-3 dB 1 MHz to 117 MHz

-1 dB 1 MHz to 64 MHz

SNR⁴

20.17 MHz 69.82 dBFS

70.17 MHz 66.95 dBFS

124.17 MHz 63.27 dBFS

SINAD⁴

20.17 MHz	69.66 dBFS
70.17 MHz	64.67 dBFS
124.17 MHz	54.64 dBFS


SFDR⁴

20.17 MHz	85.66 dBc
70.17 MHz	69.19 dBc
122.17 MHz	56.38 dBc

RX channel to RX channel isolation⁶


1 MHz	99 dB
50 MHz	78 dB
100 MHz	72 dB
150 MHz	68 dB
200 MHz	66 dB

Figure 3. DC-Coupled Passband



⁶ Worst adjacent channel with -1 dBFS input.

Figure 4. Analog Input One-Tone Spectral Measurement (20.17 MHz, -1 dBFS)



DC Power Requirements

Current Requirements

V_{EEPROM}	2 mA
--------------	------

AC-coupled build

V_{ccoA}	<1 mA
V_{ccoB}	<1 mA
P_{33V}	870 mA
P_{12V}	211 mA

DC-coupled build

V_{ccoA}	<1 mA
V_{ccoB}	<1 mA
P_{33V}	866 mA
P_{12V}	231 mA

Voltage Requirements

V_{ccoA}, V_{ccoB}	2.50 V
V_{EEPROM}	3.30 V
P_{33V}	3.3 V
P_{12V}	12 V

CLK IN

The CLK IN connector provides access to the external Reference Clock and the external Sample Clock.

External Reference Clock (CLK IN)

Input impedance	50 Ω
Coupling	AC
Input voltage (50 Ω)	1.4 V _{pp} to 4.4 V _{pp}
Input power (50 Ω)	+7 dBm to +16.8 dBm
Frequency	10 MHz

External Sample Clock (CLK IN)

Input impedance	50 Ω
Coupling	AC
Input voltage (50 Ω)	1.4 V _{pp} to 2.5 V _{pp}
Input power (50 Ω)	+7 dBm to +12 dBm
Frequency	120 MHz

Internal Clock

Internal Sample Clock

Frequency (default)	120 MHz
Reference spurs	60 dBc
Phase Noise	
10 kHz offset	-95 dBc/Hz
100 kHz offset	-115 dBc/Hz

Internal Reference

Frequency (default)	10 MHz
Stability	± 1.0 ppm
Phase Noise	
1 kHz offset	-137 dBc/Hz
10 kHz offset	-150 dBc/Hz
100 kHz offset	-155 dBc/Hz

AUX I/O (Port 0 DIO <0..3>, Port 1 DIO <0..3>, and PFI <0..3>)

Number of channels	12 bidirectional (8 DIO and 4 PFI)
Connector type	HDMI
Interface standard	3.3 V LVCMOS
Interface logic	
Maximum V_{IL}	0.8 V
Minimum V_{IH}	2.0 V
Maximum V_{OL}	0.4 V
Minimum V_{OH}	2.7 V
Maximum V_{OH}	3.6 V
Z_{out}	50 $\Omega \pm 20\%$
I_{out} (DC)	± 2 mA
Pull-down resistor	150 k Ω
Recommended operating voltage	-0.3 V to 3.6 V
Overtoltage protection	± 10 V
Maximum toggle frequency	100 MHz
+5 V maximum power	10 mA
+5 V voltage tolerance	4.2 V to 5 V

Power Draw

AC-coupled build	5.40 W
DC-coupled build	5.62 W

Physical

Dimensions	11.7 x 2.00 x 10.2 cm (4.6 x 0.8 x 4.0 in.)
Weight	317.5 g (11.2 oz)
Front panel connectors	One ganged MCX connector, one SMB connector, and one HDMI connector

Environment

Maximum altitude	2,000 m (800 mbar) (at 25 °C ambient temperature)
------------------	---

Pollution Degree	2
------------------	---

Indoor use only.

Operating Environment

Ambient temperature range	0 °C to 55 °C (Tested in accordance with IEC 60068-2-1 and IEC 60068-2-2. Meets MIL-PRF-28800F Class 3 low temperature limit and MIL-PRF-28800F Class 2 high temperature limit.)
---------------------------	--

Relative humidity range	10% to 90%, noncondensing (Tested in accordance with IEC 60068-2-56.)
-------------------------	---

Storage Environment

Ambient temperature range	-40 °C to 71 °C (Tested in accordance with IEC 60068-2-1 and IEC 60068-2-2. Meets MIL-PRF-28800F Class 3 limits.)
---------------------------	---

Relative humidity range	5% to 95%, noncondensing (Tested in accordance with IEC 60068-2-56.)
-------------------------	--

Shock and Vibration

Operating shock	30 g peak, half-sine, 11 ms pulse (Tested in accordance with IEC 60068-2-27. Meets MIL-PRF-28800F Class 2 limits.)
-----------------	--

Random vibration

Operating	5 Hz to 500 Hz, 0.3 g _{rms}
-----------	--------------------------------------

Nonoperating	5 Hz to 500 Hz, 2.4 g _{rms} (Tested in accordance with IEC 60068-2-64. Nonoperating test profile exceeds the requirements of MIL-PRF-28800F, Class 3.)
--------------	---

Compliance and Certifications

Safety

This product is designed to meet the requirements of the following electrical equipment safety standards for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1



Note For UL and other safety certifications, refer to the product label or the [Online Product Certification](#) section.

Electromagnetic Compatibility

This product meets the requirements of the following EMC standards for electrical equipment for measurement, control, and laboratory use:

- EN 61326-1 (IEC 61326-1): Class A emissions; Basic immunity
- EN 55011 (CISPR 11): Group 1, Class A emissions
- EN 55022 (CISPR 22): Class A emissions
- EN 55024 (CISPR 24): Immunity
- AS/NZS CISPR 11: Group 1, Class A emissions
- AS/NZS CISPR 22: Class A emissions
- FCC 47 CFR Part 15B: Class A emissions
- ICES-001: Class A emissions



Note In the United States (per FCC 47 CFR), Class A equipment is intended for use in commercial, light-industrial, and heavy-industrial locations. In Europe, Canada, Australia, and New Zealand (per CISPR 11), Class A equipment is intended for use only in heavy-industrial locations.



Note Group 1 equipment (per CISPR 11) is any industrial, scientific, or medical equipment that does not intentionally generate radio frequency energy for the treatment of material or inspection/analysis purposes.



Note For EMC declarations, certifications, and additional information, refer to the [Online Product Certification](#) section.

CE Compliance

This product meets the essential requirements of applicable European Directives, as follows:

- 2014/35/EU; Low-Voltage Directive (safety)
- 2014/30/EU; Electromagnetic Compatibility Directive (EMC)

Online Product Certification

Refer to the product Declaration of Conformity (DoC) for additional regulatory compliance information. To obtain product certifications and the DoC for this product, visit ni.com/certification, search by model number or product line, and click the appropriate link in the Certification column.

Environmental Management

NI is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial to the environment and to NI customers.

For additional environmental information, refer to the *Minimize Our Environmental Impact* web page at ni.com/environment. This page contains the environmental regulations and directives with which NI complies, as well as other environmental information not included in this document.

Waste Electrical and Electronic Equipment (WEEE)



EU Customers At the end of the product life cycle, all NI products must be disposed of according to local laws and regulations. For more information about how to recycle NI products in your region, visit ni.com/environment/weee.

电子信息产品污染控制管理办法（中国 RoHS）



中国客户 National Instruments 符合中国电子信息产品中限制使用某些有害物质指令 (RoHS)。关于 National Instruments 中国 RoHS 合规性信息，请登录 ni.com/environment/rohs_china。(For information about China RoHS compliance, go to ni.com/environment/rohs_china.)

Refer to the *NI Trademarks and Logo Guidelines* at ni.com/trademarks for information on National Instruments trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products/technology, refer to the appropriate location: **Help»Patents** in your software, the `patents.txt` file on your media, or the *National Instruments Patent Notice* at ni.com/patents. You can find information about end-user license agreements (EULAs) and third-party legal notices in the readme file for your NI product. Refer to the *Export Compliance Information* at ni.com/legal/export-compliance for the National Instruments global trade compliance policy and how to obtain relevant HTS codes, ECCNs, and other import/export data. NI MAKES NO EXPRESS OR IMPLIED WARRANTIES AS TO THE ACCURACY OF THE INFORMATION CONTAINED HEREIN AND SHALL NOT BE LIABLE FOR ANY ERRORS. U.S. Government Customers: The data contained in this manual was developed at private expense and is subject to the applicable limited rights and restricted data rights as set forth in FAR 52.227-14, DFAR 252.227-7014, and DFAR 252.227-7015.

© 2016 National Instruments. All rights reserved.

375442A-01 Dec16